

R3 Controller

- DMX512 channels: 1024
- Matching quantity of computer lights: 96
- Computer light rematching address code: supported
- Horizontal and vertical switching of lamps: support
- Capacitive touch screen 4.3 "
- Lamp channel reverse output: support
- Sliding mode switch of lamp channel: support
- Maximum control channels available for each computer lamp: 40 main channels+40 fine tuning channels
- Lamp library: support pearl R20 lamp library • Number of scenes that can be saved: 60
- Number of scenarios that can run simultaneously: 10
- Total number of steps in a multistep scenario: 600
- Time control of scene: fade in, fade out, LTP slide
- Number of graphics stored per scene: 5
- Push rod start scene and dimming: support
- Interlock scenario: support point control scenario: support
- Graphic generator: can generate Dimmer, P/T, RGB, CMY, Color, Gobo, Iris, Focus graphics
- Number of graphs that can be run simultaneously: 5
- Main control push rod: global, replay, lamps
- Immediate blackout: support
- Rotary table adjustment channel value: support
- Push rod adjustment channel value: support
- Push rod dimming: support
- U disk reading: supports FAT32 format
- MIDI music synchronization: support
- Create/edit light library: support
- Program backup and recovery: support
- Net weight: 9.5kg
- Weight with air case: 22kg
- Air cargo box package size: 60x55.5x30cm
- Carton packing weight: 13kg