

Technical:

Voltage: AC110-220V, 50-60HZ Power: 200W

Light source: 1 150W white light lamp bead

Pattern: 12 patterns Color: 8 colors

Rainbow: 6 colors rainbow effect

Prism: 6+12 prism

Channel: 11/13CH

Control mode: voice control, master-slave, self-propelled, DMX

X-axis: 540°

Y axis: 180°

LED Stage Lighting Operating Manual

Jade Dragon 150W Beam Light



Please read the instruction manual carefully before use

Function Description

Addr	d001-d512	512 address setting
SLnd	Auto	Host self-propelled mode
	SL 1	Slave 1
	SL 2	Slave 2
CHnd	13CH	13 channel settings
	11CH	11 channel settings
SHnd	SH 0	Effect 0 (recommended)
	SH 1	Effect 1
	SH 2	Effect 2
	SH 3	Effect 3
Soud	OFF	Voice control
	ON	Voice control on
SEnS	0-99	Voice control sensitivity adjustment
LEd	OFF	Screen goes off after 5 seconds
	ON	The screen is always on
dISP	no	show reverse
	YES	Show forward
rPAN	no	X motor rotates forward
	YES	X motor reverse
rTiL	no	Y motor forward rotation
	YES	Y motor reverse
REST	YES	system reset
t000		temperature

Channel Description

11CH	13CH	Function	Description
1	1	Horizontal operation	0-255
	2	Horizontal fine-tuning	0-255
2	3	Vertical operation	0-255
	4	Vertical fine adjustment	0-255
3	5	Horizontal and vertical speed	0-255
4	6	Dimming	0-255
5	7	Strobe	0-255
6	8	color	
		0-139	Color selection
		140-197	Color changes forward from slow to fast
		198-255	Color inversion from slow to fast
7	9	Pattern	
		0-71	fixed pattern
		72-143	pattern dither
		144-199	The pattern rotates forward from slow to fast
		200-255	Pattern reversal from slow to fast
8	10	Prism motor operation	0-99 off 100-127 on 128-255 Prism rotation from fast to slow
9	11	7 color effects	0-127 off 128-255 on
10	12	Self-propelled mode	0-29 Other channel functions
			30-59 Self-propelled 1 60-89 Self-propelled 2
			90-119 self-propelled 3 120-149 self-propelled 4
		Voice control mode	150-179 Voice control 1 180-209 Voice control 2 210-239 Voice control 3 240-255 Voice control 4
11	13	reset	250-255 (5 second)